

DC to AC POWER INVERTER

This product is designed to convert 12V DC power from any cigarette lighter to 220 50Hz AC with 150W continuous power to a maximum of 250W surge power. Ideal for easy operation and exceptional value.

Features: Output short circuit protection, over heat protection, over load protection, DC input reverse polarity protection, to protect your battery it also has DC under voltage protection.








Application for:

- ❑ Digicam, Camcorder
- ❑ Laptop, PDA, Smart Phone
- ❑ DVD/VCD/CD Player, 21" TV
- ❑ Walkman, Stereos, Radio
- ❑ PS1, PS2, Video Games, Toys
- ❑ Lamps, Neon, Fans
- ❑ Cellular Phone/HP
- ❑ Active Speaker, Sound System
- ❑ Cordless Phone, Fax Machine
- ❑ Printer, Scanner
- ❑ Electric shaver
- ❑ And many more.

Technical specification:



Model Number ALLways 150

OUTPUT RECEPTACLES			Voltage In	12VDC
			Voltage Out	220V AC
Type-1	Type-2	Type-3	Continuous Power	140W, 150 watts 30 minutes
			Peak Power	250W
Type-4	Type-5	Type-6	Output Frequency	50Hz
			Output Waveform	Modified Sine Wave
Type-7			No Load Current Draw	Less than 0.5A
			Efficiency	90%
			Fuse	15A
			Weight	0.8kg
			Dimension	135 x 123 x 61mm (LxWxH)

