

## DC - AC POWER INVERTER 100 Watts

This product is designed to convert 12V DC power from any cigarette lighter to 220 50Hz AC with 100W continuous power to a maximum of 200W surge power. Ideal for easy operation and exceptional value.

Features: Output short circuit protection, over heat protection, over load protection, DC input reverse polarity protection, to protect your battery it also has DC under voltage protection.

Application for:

- Digicam, Camcorder
- PDA, Smart Phone
- DVD/VCD/CD Player
- Walkman, Stereos, Radio
- PS1, Video Games, Toys
- Lamps, Neon, Fans
- Cellular Phone/HP
- Active Speaker
- Cordless Phone, Fax Machine
- Printer, Scanner
- Electric shaver
- And many more.

Technical specification:



Model Number	KV-100
Voltage In	12VDC
Voltage Out	220VAC
Continuous Power	100W
Peak Power	200W
Output Frequency	50Hz
Output Waveform	Modified Sine Wave
No Load Current Draw	0.1A
Efficiency	90%
Fuse	15A
Casing	Aluminium
Weight	0.45kg
Dimension	135 x 75 x 40mm (LxWxH)

### OUTPUT RECEPTACLES



Type-1 Type-2 Type-3



Type-4 Type-5 Type-6



Type-7

