

DC to AC POWER INVERTER + CHARGER

This product is designed to convert 12V DC from battery power to 220V 50Hz AC with 1000W continuous power to a maximum of 2000W surge power. Ideal for easy operation and exceptional value.


Features: Output short circuit protection, over heat protection, over load protection, DC input reverse polarity protection, to protect your battery it also has DC under voltage protection.

Application for:

- ❑ Laptop, PDA, Smart Phone
- ❑ DVD/VCD/CD Player, 21" TV
- ❑ PS1, PS2, Video Games, Toys
- ❑ Lamps, Neon, Fans
- ❑ Emergency lamp
- ❑ Blender, Mixer
- ❑ Hand Drill, Power tools
- ❑ Active Speaker, Sound System
- ❑ Personal Computer
- ❑ Printer, Scanner
- ❑ Electric shaver
- ❑ And many more.



OUTPUT RECEPTACLES



Technical specification:

Model Number	KV-1000C
Voltage In	12VDC
Voltage Out	220V AC
Continuous Power	1000W
Peak Power	2000W
Output Frequency	50Hz or 60Hz
Output Waveform	Modified Sine Wave
No Load Current Draw	0.8A
Charging Current	5A
Efficiency	90%
Fuse	3 x 30A
Weight	1.95kg
Dimension	265 x 150 x 60mm (LxWxH)