

DC - AC POWER INVERTER 80 Watts

This product is designed to convert 12V DC power from any cigarette lighter to 220 50Hz AC with 80W continuous power to a maximum of 150W surge power. Ideal for easy operation and exceptional value.

Features: Output short circuit protection, over heat protection, over load protection, DC input reverse polarity protection, to protect your battery it also has DC under voltage protection.

Application for:

- Digicam, Camcorder
- PDA, Smart Phone
- DVD/VCD/CD Player,
- Walkman, Stereos, Radio
- PS1, Video Games, Toys
- Lamps, Neon
- Cellular Phone/HP
- Cordless Phone, Fax Machine
- Printer, Scanner
- Electric shaver
- Mini Fan
- And many more.

Technical specification:



Model Number	KV-80
Voltage In	12VDC
Voltage Out	220VAC
Continuous Power	80W
Peak Power	150W (1 cycle)
Output Frequency	50Hz
Output Waveform	Modified Sine Wave
No Load Current Draw	0.1A
Efficiency	90%
Fuse	10A
Casing	ABS Plastics
Weight	0.16kg
Dimension	115 x 60 x 35mm (LxWxH)

OUTPUT RECEPTACLES



Type-1 Type-2

