

DC-AC POWER INVERTER 1200W 48DC INPUT

This product is designed to convert 48V DC power to 220V 50Hz AC with 1200W continuous power to a maximum of 2000W surge power. Ideal for easy operation and exceptional value.

Features: Output short circuit protection, over heat protection, over load protection, DC input reverse polarity protection, to protect your battery it also has DC under voltage protection.

Application for:










- Modem
- Router, HUB, Switch
- GPS
- Lamps, Neon, Fans
- Laptop, PC and peripheral
- Power tools
- Active Speaker, Sound System
- Cordless Phone, Fax Machine
- Printer, Scanner
- And many more.

Technical specification:

Model Number

ALLways 1200-48



OUTPUT RECEPTACLES		Voltage In	48VDC
		Input Current	30A max for 48VDC
Type-1	Type-2	Input voltage regulation	40 – 60 VDC
	Voltage Out		220V AC
Type-3	Continuous Power		1000W, 1200 watts 30 minutes
		Peak Power	2000W
Type-4	Type-5	Output Frequency	50Hz
	Output Waveform		Modified Sine Wave
Type-6	No Load Current Draw		Less than 0.5A
	Efficiency		90%
Type-7	EMI Standard		CE class – B/EMC
		Weight	4.6kg
		Dimension	395 x 186 x 76mm (LxWxH)