

DC - AC POWER INVERTER 150 Watts

This product is designed to convert 12V DC power from any cigarette lighter to 220 50Hz AC with 100W continuous power to a maximum of 200W surge power. Ideal for easy operation and exceptional value.

Features: Output short circuit protection, over heat protection, over load protection, DC input reverse polarity protection, to protect your battery it also has DC under voltage protection.

Application for:


- Digicam, Camcorder
- Laptop, PDA, Smart Phone
- DVD/VCD/CD Player, 14" TV
- Walkman, Stereos, Radio
- PS1, PS2, Video Games, Toys
- Lamps, Neon, Fans
- Cellular Phone/HP
- Active Speaker, Sound System
- Cordless Phone, Fax Machine
- Printer, Scanner
- Electric shaver
- And many more.

Technical specification:



Model Number	KV-150
Voltage In	12VDC
Voltage Out	220VAC
Continuous Power	150W
Peak Power	300W
Output Frequency	50Hz
Output Waveform	Modified Sine Wave
No Load Current Draw	0.2A
Efficiency	90%
Fuse	20A
Casing	Aluminium
Weight	0.48kg
Dimension	135 x 75 x 40mm (LxWxH)

OUTPUT RECEPTACLES



Type-1 Type-2 Type-3



Type-4 Type-5 Type-6



Type-7

