

DC to AC POWER INVERTER

This product is designed to convert 48V DC power to 220 50Hz AC with 500W continuous power to a maximum of 1000W surge power. Ideal for easy operation and exceptional value.

Features: Output short circuit protection, over heat protection, over load protection, DC input reverse polarity protection, to protect your battery it also has DC under voltage protection.

Application for:

- ❑ Routers, Hub, Switch
- ❑ Modem
- ❑ Digicam, Camcorder
- ❑ Laptop, PDA, Smart Phone
- ❑ DVD/VCD/CD Player, 21" TV
- ❑ Lamps, Neon, Fans
- ❑ Hand drill
- ❑ Cellular Phone/HP
- ❑ Active Speaker, Sound System
- ❑ Cordless Phone, Fax Machine
- ❑ Printer, Scanner
- ❑ GPS
- ❑ Blender, Mixer
- ❑ And many more.



Technical specification:

	Model Number	ALLways-500
	Voltage In	48VDC , Range: 40 – 60VDC
	Voltage Out	220V AC
	Continuous Power	500W
	Peak Power	1000W
	Output Frequency	50Hz
	Output Waveform	Modified Sine Wave
	No Load Current Draw	0.6A
	Efficiency	90%
	EMI Standard	CE Class - B/EMC
	Weight	2.7kg
	Dimension	220 x 186 x 76mm (LxWxH)

OUTPUT RECEPTACLES

